

Inform

ECN D34xx-B1 / D34xx-B2

"KabyLake" Update

ECN-No. SBOEM-D34xx-190115

Reason for ECN: Support for *KabyLake* processor series (Intel 7th generation) added

New Core BIOS required -> new mainboard versions D34xx-B2.
 Support for DDR4-2400 with *KabyLake* processors possible.

Current Part No. / Revision	New Part No. / Revision
D3400-B11 / GS3	D3400-B22 / GS1
D3410-B11 / GS3	D3410-B22 / GS1
D3401-B11 / GS3	D3401-B21 / GS1
D3402-B11 / GS3	D3402-B21 / GS1
D3417-B11 / GS3	D3417-B21 / GS1

Shipping details: Mass production shipment of the new mainboard version is expected from March 2017 (D3400-B2 / D3410-B2 / D3401-B2 / D3402-B2) resp. April 2017 (D3417-B2)

Features:

	Mainboard Version	
	D34xx-B1	D34xx-B2
UDIMM DDR4-2133 / DDR4-2400	x / - ¹⁾	x / x
Intel® Core™ i7-i5-i3 processor series – 6 th gen. / 7 th gen.	x / -	x / x
Intel® Pentium® / Celeron® processor series – 6 th gen. / 7 th gen.	x / -	x / x
Intel® Xeon® processor series E3-12xx V5 / E3-12xx V6 (D3417 only!)	x / -	x / x
Skylake Drivers / KabyLake Drivers (MS Windows)	x / x	- / x

1) DDR4-2400 modules can be used, but they will operate at reduced speed

Operating Systems tested & released by Fujitsu:

Mainboard Version	Win XP32/64	Win Vista	Win 7-32	Win 7-64	Win 8.1-32	Win 8.1-64	Win 10 -64	Windows Server 2008 R2 (64)	Windows Server 2012 R2 (64)
D34xx-B1 + Skylake (= 6 th gen.) processor	---	---	X	X	---	X	X	---	---
D34xx-B1 + KabyLake (= 7 th gen.) processor	Not possible! ¹⁾								
D34xx-B2 + Skylake (= 6 th gen.) processor	---	---	X ²⁾	X ²⁾	---	X	X	---	---
D34xx-B2 + KabyLake (= 7 th gen.) processor	---	---	Not supported by Intel! ³⁾		Not supported by Intel! ³⁾		X	---	---

1) D34xx-B1 cannot be upgraded to D34xx-B2; KabyLake processor support on D34xx-B1 is NOT possible

2) MS Windows 7 test & release for D34xx-B2 scheduled for Q2/2017

3) No MS Windows 7 / 8.1 driver support for KabyLake processor integrated graphics

Common driver link:

ftp://ftp.ts.fujitsu.com/pub/Mainboard-OEM-Sales/Products/Mainboards/Industrial&ExtendedLifetime/D3402-B_D3417-B/Drivers_D3402_D3417/

Fujitsu highly recommends to use the latest released drivers for D34xx-B2 mainboards.

Date	Revision Overview
01/2017	KabyLake Update D34xx-B2

Published by department
Systemboard OEM Sales

OEM FTP
<ftp://ftp.ts.fujitsu.com/pub/Mainboard-OEM-Sales/>

Oem-marketing@ts.fujitsu.com

<http://www.fujitsu.com/fts/products/computing/pc/accessories/mainboards/>

All rights reserved, including intellectual property rights. Technical data subject to modifications and delivery subject to availability. Any liability that the data and illustrations are complete, actual or correct is excluded. Designations may be trademarks and/or copyrights of the respective manufacturer, the use of which by third parties for their own purposes may infringe the rights of such owner. For further information see ts.fujitsu.com/terms_of_use.html
 © Copyright Fujitsu Technology Solutions GmbH 2017